

## Product Introduction

This smart scene button utilizes ultra-low power ZigBee technology, serving as both an emergency button and a trigger for home automation scenes.

## Features

- One-touch emergency alert
- One-touch automation scene trigger
- Ultra-low power consumption with long battery life
- Easy installation with no wiring required
- Sleek and stylish design



## Specification

- Model: MIR-SO100
- Communication protocol: ZigBee 3.0
- Input voltage: 3V/DC
- Low voltage alert threshold:  $2.6V \pm 0.2V$
- Standby current:  $\leq 5\mu A$
- Operating current:  $\leq 30mA$
- Battery type: CR2032
- Battery life: Over one year (20 uses/day)
- Operating temperature:  $-10$  to  $55^{\circ}C$
- Installation method: Ceiling or wall mount
- Dimensions:  $\Phi 50 \times 16mm$
- Certification: CE

## Networking method

1. Use a thin tool to open the device's back cover and remove the insulation sheet to power on the device.
2. Press and hold the reset button for about 5 seconds until the indicator light flashes rapidly, indicating that it has entered pairing mode.
3. Add the device to the network via the gateway.

## Product Dimension Diagram (mm)

